

Generator Control Panel



ENGINE & GENERATOR CONTROLS

P2 AND P3 SERIES



P2

8.3" (w) x 8.1" (h) x 7.5" (d)
(2.70" panelboard style meters)



P3

P3: 16.1" (w) x 5.25" (h) x 8.4" (d)
(3.5" panelboard style meters)

STANDARD FEATURES

- ABS UV protected corrosion proof cabinet and corrosion resistant hardware.
- 2% accuracy ammeter, voltmeter and frequency meters with required fusing
- Volt/Amps phase selector switch
- Panel Includes: current transformers, vibration isolators, and wiring schematics.

P2 or 3 $\frac{\quad}{1}$ $\frac{\quad}{2}$ $\frac{\quad}{3}$

1. Voltage
A = 480 C = 240 - 208

2. Amps (Example)
(Format= amps/10)
005 = 50 amp
010 = 100 amp
015 = 150 amp
150 = 1500 amp

3. . PH/FRQ
A = 1/60
B = 1/50
C = 3/60
D = 3/50

PART NUMBER KEY

National Marketing and Distribution by Davidson Sales Co.

839 Bill France Blvd., Daytona Beach, FL 32117
Phone: (386)274-2079 Fax: (386)274-2279 www.davidsonsales.com

Revised 5/17